



Bill of Materials for XTALL Daughter Board

Resistors	Used where	Quantity
75 3W 5%	R1	1
1.00k 1%	R2, R3	2
10.0k 1%	R4, R6, R8, R10	4
499 1%	R5, R7, R9, R11	4

Capacitors	Used where	Quantity
4.7uF ceramic	C1, C5	2
0.01uF, SMT1206	C2, C3, C4, C6, C7	5

ICs	Used where	Quantity
LP2992AIM5-3.3v	U1 on bottom of board	1
12F683 and socket	U2	1
Si570	U3 (not in kit)	1

Switch	Used where	Quantity
4-position DIP switch	SW1	1

Circuit board	Quantity
XTALL v1.0	1

Kit building notes:

Order of mounting parts on the circuit board:

SMT capacitors C2, C3, C4, C6, C7 on bottom of board

1) Five-pin SMT voltage regulator, U1, on bottom of board

Exercise care in mounting U1 on the circuit board.

Make sure U1 leads are well centered on their pads before tacking part in place by careful soldering of one lead. Apply heat to pin to reposition U1 and when properly positioned carefully solder the other leads. Use solder wick to remove excess solder or solder bridges between pins.

2) U3, Si570, on top of board with careful soldering as with U1

3) Resistors R2 through R11 on top of board

4) Capacitors C1 and C5 on top of board

5) Socket for U2 on top of board

6) DIP switch pack, SW1, on top of board

7) Power resistors R1 mounted 1/2 inch above top of board, body parallel to the top of board.

SoftRock Projects

XTALL daughter board

Tony, KB9YIG

Rev 1.0

2/25/2008

Page 1 of 1